# FFLED18MS

Featuring 180 degree outward motion detection, this package provides an attractive and cost effective solution for applications that call for a fixture with a smaller, less prominent sensor.


LED Info Driver Info

**Constant Current** Watts: 18 Type: 5000K (Cool) 120V: Color Temp: 0.2 A Color Accuracy: 70 208V: 0.15 A L70 Lifespan: 240V: 0.13 A LM79 Lumens: 1,624 277V: 0.11 A Efficacy: 74 LPW Input Watts: 22W Efficiency: 82%

Color: Bronze

Weight: 5.3 lbs





# **Technical Specifications**

#### **UL Listing:**

Suitable For Wet Locations. Suitable for mounting within 4ft of the ground

# **NEMA Type:**

7H x 6V Beam Spread

## Airflow:

Patent pending Airflow technology heat sink for superior cooling

### LEDs:

18 Watt high performance LEDs

#### Driver:

Constant Current, Class 2, 100 - 277V, 50 - 60 Hz, 100 - 277VAC 0.4 Amps

# **Input Watts:**

22

### **Fixture Efficacy:**

73 Lumens per Watt

### **Surge Protection:**

Withstands up to 3000 volts

# **Ambient Temperature:**

Suitable for use in 40C ambient temperatures.

### **Cold Weather Starting:**

The minimum starting temperature is -40F/-40C.

# **Heatsink Housing:**

Die-cast aluminum housing, lens frame and mounting arm

# Mounting:

Heavy-duty mounting arm with O ring seal & stainless steel screw

### **Color Stability:**

RAB LEDs exceed industry standards for chromatic stability.

# **Color Accuracy:**

**70 CRI** 

# **Color Temperature (Nominal CCT):**

5000K

### **Color Uniformity:**

RAB's range of CCT (Correlated Color Temperature) follows the guidelines of the American National Standard for (SSL) Products, ANSI C78.377-2008.

#### Reflector:

Semi-specular anodized aluminum

# Gaskets:

High-temperature silicone gaskets

#### Finish:

Chip and fade resistant polyester

### **Green Technology:**

Mercury and UV free

# IESNA LM-79 & LM-80 Testing:

RAB LED luminaires have been tested by an independent laboratory in accordance with IESNA LM-79 and LM-80, and have received the Department of Energy Lighting Facts label.

#### California Title 24:

FFLED18 complies with California Title 24 building and electrical codes.

# Warranty:

5 year sensor warranty



Tech Help Line: 888 RAB-1000

Email: sales@rabweb.com

On the web at: www.rabweb.com

Note: Specifications are subject to change without notice

#### FFLED18MS - continued

#### Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws.

# **Country of Origin:**

Designed by RAB in New Jersey and assembled in the USA by IBEW Local 3

### **Buy American Act Compliant:**

This product is a COTS item manufactured in the United States, and is compliant with the Buy American Act.

# **Recovery Act (ARRA) Compliant:**

This product complies with the 52.225-21 "Required Use of American Iron, Steel, and Manufactured Goods--Buy American Act-- Construction Materials (October 2010)

### **Trade Agreements Act Compliant:**

This product is a COTS item manufactured in the United States, and is compliant with the Trade Agreements Act.

#### **GSA Schedule:**

This product is suitable for listing on the GSA Schedule of the US General Services in accordance with FAR Subpart 25.4

# Compatibility:

Compatible with most electronic ballasts. Not compatible with instant start ballasts.

### Voltage:

120 volts AC 60 Hz.

### **Time Adjustment:**

5 seconds to 15 minutes

#### **Quick Test Time:**

5 second test time for fast installation. Works day or night.

# "No Hands" Auto Testing:

Auto mode starts after 4 minutes of testing. No adjustment needed.

# **Photoelectric Control:**

Deactivates lights during daylight. Fully adjustable for 24 hour operation or custom applications.

#### **Manual Override:**

Double flip wall switch logic prevents activation by brief power outages. Resets after 8 hours. No extra wiring needed.

# **LED Detection Indicator:**

LED glows red day & night for "on guard" deterrence.

#### **RF Immunity:**

Circuits fully shielded for maximum radio frequency immunity.

# Ratings:

5 amps

### **Power Consumption:**

Negligible

### Time Delay:

5 seconds to 15 minutes

### **Manual Switch:**

None

### **Ambient Light Sensing:**

Adjustable

### Adjustments:

Time, ambient light & sensitivity

#### **Detection:**

180 detection pattern

### **Sensor Switching Capacity:**

5 Amps, 450 Watts LED @ 120 Volts 0.8pF Driver; 5 Amps, 300 Watts LED @ 120 Volts 0.5pF Driver