

# Recommended Dimmers for CR Series LED Downlights

## Including CR6-575L, CR6-800L and CR4-575L\*

Cree, Inc.  
 Phone: (800) 236-6800  
 Fax: (262) 504-5415  
[www.cree.com/lighting](http://www.cree.com/lighting)

Manufacturer	Series/Model	Part Number(s)	Type	Min/Max Fixtures Per Dimmer
Leviton®	Decora®	6631	600W Incandescent	2 - 8
	Illumatech®	IPI06	600W Incandescent	2 - 8
	Trimatron®	6683	600W Incandescent	2 - 8
	Vizia®	VPI06, RPI06	600W Incandescent	3 - 8
	Acenti®	ATI06-1LW	600W Incandescent	3 - 8
Lutron®	Nova T®	NTELV-600	600W Electronic Low Voltage	1 – 10
	Nova®	NLV-1503P	1500W Magnetic Low Voltage	3 – 21
	Skylark®	S-600 or S-600P	600W Incandescent	2 - 8
	Skylark®	SLV-600P	600W Magnetic Low Voltage	1 -10
	Skylark®	SELV-300P	300W Electronic Low Voltage	1 - 10
	Skylark®	SF-10P or SF-103P	8A 3-Wire Fluorescent	1 – 12
	Diva®	DV-600P, DV603P	600W Incandescent	2 – 8
	Diva®	DV-10P	1000W Incandescent	2 – 15
	Diva®	DVLV-600P	600W Magnetic Low Voltage	1 – 10
	Diva®	DVELV-300P	300W Electronic Low Voltage	1 – 10
	Maestro Wireless	MRF2-6ND	600W Incandescent	1 – 8
	RadioRA 2	RRD-10ND	Incandescent	1 – 12
	RadioRA 2	RRD-8ANS	Incandescent	1 – 12
RadioRA 2	RRD-6NA	Incandescent	1 – 36	

The CR Series LED Downlights is designed to be dimmed with standard incandescent type dimmers, and is also compatible with most Magnetic Low Voltage (MLV) and Electronic Low Voltage (ELV) type dimmers. Due to the custom electronic design and the minimum loading requirements of most dimmers, it should generally be treated as a 75W load when sizing dimmers. The recommended list is generated from laboratory testing, and the results can vary in certain field applications due to a number of factors. The absence of a dimmer from this chart does not necessarily imply incompatibility. Please reference the dimmer manufacturer's instructions for installation.

### APPLICATION NOTES

- Due to an electronic characteristic known as Repetitive Peak Current, which results from inrush current at the phase cut, Cree downlights should be treated as a 75W load for sizing purposes when used with dimmers.
- In situations where there are multiple dimming circuits sharing the same breaker feed, ELV dimmers should be used.

\*The presence of a dimmer on this chart is not a guarantee or warranty of the compatibility of the CR Series LED Downlights in any particular installation. The absence of a dimmer from this chart does not necessarily imply incompatibility. Please reference the dimmer manufacturer's instructions for installation and further product information.